



Cisco Systems Confidential

Voice Is Not A Network

- Voice is an Application
- Complete understanding of Voice Application fundamentals helps us to design and build better Networks



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

3

Objective

**To Prepare the Data
Communications Professional
for Voice and Data Network
Integration by Providing Voice
Technology Fundamentals**

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

4

Agenda

- **Basic Analog Telephony**
- **Basic Digital Telephony**
- **Voice Coding and Compression Techniques**
- **Voice Transport and Delay**
- **Supplemental Slides: Digital Voice Signaling Techniques**

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

5

Telephony Equipment

- **Telephone set**
- **Key system**
 - Optimizes use of telephone sets to lines
 - Mechanical to electronic
 - Two to ten telephone handsets is typical
- **PBX (Private Branch Exchange)**
 - Advanced features and call routing
 - Tens to hundreds of telephone handsets
- **Central office switch**


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

6

Analog Telephony— Connection Basics




401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

7

Basic Call Progress: On-Hook



401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

8

Cisco Systems Confidential

Basic Call Progress: Off-Hook




401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

9

Basic Call Progress: Dialing




401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

10

Basic Call Progress: Switching




401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

11

Basic Call Progress: Ringing




401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

12

Basic Call Progress: Talking



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

13

Analog Telephony—Signaling

- Supervisory
- Addressing
- Call progress


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

14

Analog Telephony— Supervisory Signaling



- **Loop start**
 - Almost all telephones
 - Current flow sensed
- **Ground start**
 - Switch Trunk Lines
 - Momentary ground ring lead


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

15

Loop Start



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

16

Cisco Systems Confidential

E&M Signaling

- **PBXs, switches**

Separate signaling leads for each direction

E-Lead (inbound direction)

M-Lead (outbound direction)

Allows independent signaling

State	E-Lead	M-Lead
On-Hook	Open	Ground
Off-Hook	Ground	Battery Voltage

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

17


Signaling and Addressing



Dial Pulse



DTMF



ISDN

Analog Transmission
“In-Band” Signaling
0–9, *, # (12 Digits)

Digital Transmission
“Out-of-Band”
Message-Based
Signaling


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

18

Pulse Dialing



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

19

Tone Dialing

Dual Tone Multifrequency (DTMF)				
	1209	1336	1477	1633
697	1	2	3	A
770	4	5	6	B
852	7	8	9	C
941	*	0	#	D

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

20

Cisco Systems Confidential

Voice Channel Bandwidth



401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

21

Switching Systems

Manual Control—Switch/Cord Boards



401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

22

Cisco Systems Confidential

Local Access Network




401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

23

PSTN Network Hierarchy



401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

24

Cisco Systems Confidential

Types of Voice Circuits




401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

25

Echo in Voice Networks



401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

26

Cisco Systems Confidential

Normal Signal Flow



- Two- to four-wire hybrid combines receive-and transmit-signals over the same pair
- Two-wire impedance must match four-wire impedance

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

27

How Does Echo Happen?

Echo Is Due to a Reflection



**Impedance Mismatch at the 2w-4w Hybrid
Is the Most Common Reason for Echo**

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

28

Echo Is Always Present

Echo as a Problem Is a Function of the Echo Delay, and the Magnitude of the Echo



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

29

Ways to Defeat Echo

- **Increase the loss in the echo path**
Can often be the solution
Disadvantage: static setting and reduces the signal strength of the speaker
- **Echo suppresser**
Acts like a noise gate, effectively making communications half-duplex

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

30

Echo Canceled

Most Effective Means for Removing Echo



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

31

Summary

- Information exchange based on voltage, current flow, grounding, and so on
- Analog voice technology dates back to the late 1800s

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

32

Agenda

- **Basic Analog Telephony**
- **Basic Digital Telephony**
- **Voice Coding and Compression Techniques**
- **Voice Transport and Delay**
- **Supplemental Slides: Digital Voice Signaling Techniques**


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

33

Digital Telephony



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com


34

Cisco Systems Confidential

Digital Telephony

Pulse Code Modulation—Nyquist Theorem

Voice Bandwidth =
200 Hz to 3400 Hz



Codec Technique

| = Sample
8 bits per sample
8 kHz (8,000 Samples/Sec)

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

35


Pulse Code Modulation— Analog to Digital Conversion

A—Law (Europe)



Stage 1

μ—Law (USA)



10010011011

Quantizing Stage

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

36

Cisco Systems Confidential

Time Division Multiplexer Example: T1 Channel Bank



401

0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

37

DS1 Superframe (D4) Format

- 193rd bit of each frame used for frame synchronization
- D4 framing is 12 frames
- D4 framing pattern is: 100011011100
- Channel Associated Signaling (CAS) robs the LSB of every byte in frames 6 and 12 for AB bits
- Common Channel Signaling (ISDN) uses TS 24

Frame Number	Framing Bits	Bit Use in Each Channel Time Slot		Signaling—Bit Use Options		
	Framing Bit Value	Traffic	Signaling	T	2	4
1	1					
2	0					
3	0					
4	0					
5	1					
6	1	Bits 1-7	Bit 8	*	A	A
7	0					
8	1					
9	1					
10	1					
11	0					
12	0	Bits 1-7	Bit 8	*	A	B

401

0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

38

Extended Superframe (ESF)

Frame Number	S Bits			Bit Use in Each Channel Time Slot		Signaling—Bit Use Options			
	Fe	DL	BC	Traffic	Signaling	T	2	4	16
1	—	m	—						
2	—	m	C1						
3	—	m	—						
4	0	—	—						
5	—	m	—						
6	—	—	C2	Bits 1–7	Bit 8	*	A	A	A
7	—	m	—						
8	0	—	—						
9	—	m	—						
10	—	m	C3						
11	—	m	—						
12	1	—	—	Bits 1–7	Bit 8	*	A	B	B
13	—	m	—						
14	—	m	—						
15	—	m	—						
16	0	—	—						
17	—	m	—						
18	—	—	C5	Bits 1–7	Bit 8	*	A	A	C
19	—	m	—						
20	1	—	—						
21	—	m	—						
22	—	m	C6						
23	—	m	—						
24	1	—	—	Bits 1–7	Bit 8	*	A	B	D

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

39

Digital Signaling Schemes

Channel Associated Signaling Extended Superframe



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.


www.cisco.com

40

Digital Signaling Schemes

Common Channel Signaling

Extended Super Frame



**"In-Band" Audio
Address Signaling
(DTMF)**

**64 Kbps Signaling
Channel in TS24
of Each Frame
(e.g. ISDN D Channel
Q.931 Messages)**


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

41

Digital Telephony— Synchronization



- **Bit synchronization**
Primary reference source
Ones density
- **Time-slot synchronization**
Bits/bytes/channels
- **Frame alignment**
193rd Bit Pattern

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

42

Digital Telephony—Synchronization

One Multiframe (ESF)




401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

43

Synchronization—Traditional Network Clocking Strata



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

44

Cisco Systems Confidential

Agenda

- **Basic Analog Telephony**
- **Basic Digital Telephony**
- **Voice Coding and Compression Techniques**
- **Voice Transport and Delay**
- **Supplemental Slides: Digital Voice Signaling Techniques**

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

45

Voice Coding and Compression

- **Speech-coding schemes**
- **Subjective impairment analysis: mean opinion scores**
- **Digitizing voice**
- **Voice compression**
 - ADPCM**
 - CELP (LD-CELP and CSA-CELP)**
 - Silence removal techniques (DSI using VAD)**


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

46

Voice Compression Technologies



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

47

Speech-Coding Schemes

- **Waveform coders**
 - Non-linear approximation of the actual waveform
 - Examples: PCM, ADPCM
- **Vocoders**
 - Synthesized voice
 - Example: LPC
- **Hybrid coders**
 - Linear waveform approximation with synthesized voice
 - Example: CELP


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

48

Subjective Impairment Analysis: Mean Opinion Scores



Score	Quality	Description of Impairment
5	Excellent	Imperceptible
4	Good	Just Perceptible, not Annoying
3	Fair	Perceptible and Slightly Annoying
2	Poor	Annoying but not Objectionable
1	Bad	Very Annoying and Objectionable


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

49

Measuring Mean Opinion Scores: ITU P.800 Series



401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

50

Digitizing Voice: PCM Waveform Encoding Review

- **Nyquist Theorem: sample at twice the highest frequency**
Voice frequency range: 200-3400 Hz
Sampling frequency = 8000/sec (every 125µs)
Bit rate: $(2 \times 4 \text{ kHz}) \times 8 \text{ bits per sample}$
= 64,000 bits per second (DS-0)
- **By far the most commonly used method**





401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

51

Nonlinear vs. Linear Encoding




401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

52

Voice CODECs: Waveform Coders



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

53

Voice Compression

- **Objective: reduce bandwidth consumption**
Compression algorithms are optimized for voice
Unlike data compression: these are “loose”
- **Drawbacks/tradeoffs**
Quantization distortion
Tandem switching degradation
Delay (echo)

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

54

Voice Compression—ADPCM

- **Adaptive Differential Pulse Code Modulation**

Waveform coding scheme

Adaptive: automatic companding

Differential: encode the changes between samples only

Rates and bits per sample:

32 Kbps = 8 Kbps x 4 bits/sample

24 Kbps = 8 Kbps x 3 bits/sample

16 Kbps = 8 Kbps x 2 bits/sample

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

55

Voice Compression—CELP

- **Code excited linear predictive**
- **Very high voice quality at low-bit rates, processor intensive, use of DSPs**
- **G.728: LD-CELP—16 Kbps**
- **G.729: CSA-CELP—8 Kbps**

G.729a variant— “stripped down” 8 kbps (with a noticeable quality difference) to reduce processing load, allows two voice channels encoded per DSP


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

56

Voice CODECs: Hybrid Coders




401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

57

G.729



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

58

Digital Speech Interpolation (DSI)

- Voice Activity Detection (VAD)
- Removal of voice silence
- Examines voice for power, change of power, frequency and change of frequency
- All factors must indicate voice “fits into the window” before cells are constructed
- Automatically disabled for fax/modem


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

59

Voice Activity Detection



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

60

Cisco Systems Confidential

Bandwidth Requirements

Voice Band Traffic

Encoding/ Compression	Result Bit Rate
G.711 PCM A-Law/ μ -Law	64 kbps (DS0)
G.726 ADPCM	16, 24, 32, 40 kbps
G.729 CS-ACELP	8 kbps
G.728 LD-CELP	16 kbps
G.723.1 CELP	6.3/5.3 kbps Variable

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

61

Agenda

- **Basic Analog Telephony**
- **Basic Digital Telephony**
- **Voice Coding and Compression Techniques**
- **Voice Transport and Delay**
- **Supplemental Slides: Digital Voice Signaling Techniques**

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

62

Voice Network Transport

- **Voice Network Transport is typically TDM circuit-based:**
 - T1/E1
 - DS3/E3
 - SONET (OC-3, OC-12, etc.)
- **But can also be packet-based:**
 - ATM
 - Frame Relay
 - IP

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

63

Data Is Overtaking Voice

Evolution from TDM-based transport to packets/cells or a combination



Source: Electronicast

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

64

The Tyranny of the DS0

- Switching and transport based on circuits
- Rigid structure yields high cost for packet




401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

65

TDM Transport Efficiency



- Wasted bandwidth
- No congestion


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

66

Packet Transport Efficiency



- High bandwidth efficiency
- Congestion management


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

67

Delay



401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

68

Cisco Systems Confidential

Delay Variation—"Jitter"



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

69

Voice Delay Guidelines

One Way Delay (msec)	Description
0–150	Acceptable for Most User Applications
150–400	Acceptable Provided That Administrations Are Aware of the Transmission Time Impact on the Transmission Quality of User Applications
400+	Unacceptable for General Network Planning Purposes; However, It Is Recognized That in Some Exceptional Cases This Limit Will Be Exceeded

ITU's G.114 Recommendation

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

70

Delay in Perspective

Cumulative Transmission Path Delay



401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

71

Fixed Delay Components

- Propagation Delay
- ↘ Serialization Delay—Buffer to Serial Link
- Processing Delay



- Propagation—Six microseconds per kilometer
- Serialization
- Processing
 - Coding/compression/decompression/decoding
 - Packetization


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

72

Variable Delay Components



- Queuing delay
- Dejitter buffers
- Variable packet sizes

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

73

An Example

- **Assumptions:**

We have eight trunks

We are going to use CS-ACELP that uses 8 Kbps per voice channel

Our uplink is 64 Kbps

Voice is using a high priority queue and no other traffic is being used


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

74

Delay Calculation



	Fixed Delay	Variable Delay
Coder Delay G.729 (5 msec Look Ahead)	5 msec	
Coder Delay G.729 (10 msec per Frame)	20 msec	
Packetization Delay—Included in Coder Delay		
Max Queuing Delay 64 kbps Trunk		21 msec
Serialization Delay 64 kbps Trunk	3 msec	
Propagation Delay (Private Lines)	32 msec	
Network Delay (e.g., Public Frame Relay Svc)		
Dejitter Buffer	50 msec	
Total	110 msec	

Variable Delay Component

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

82

Variable Delay Calculation

- We have eight trunks, so in the worst case we will have to wait for seven voice calls prior to ours
- To put one voice frame out on a 64Kbps link takes 3msec
- 1 byte over a 64Kbps link takes 125 microseconds. We have a 20 byte frame relay frame with 4 bytes of overhead. $125 * 24 = 3000$ usecs or 3 msec
- Does not factor in waiting for a possible data packet or the impact of variable sized frames
- Assumes voice prioritization of frames

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

76

Delay Calculation

	Fixed Delay	Variable Delay
DELAY #1		
Coder Delay G.729	25 msec	
Packetization Delay (Included in Coder Delay)		
Max Queuing Delay 64 kbps Trunk		21msec
Serialization Delay 64 kbps Trunk	3 msec	
Propagation Delay (Private Lines)	32 msec	
Dejitter Buffer	50 msec	
Tandem Switch	—	
Delay #1 Total	110 msec	



401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

77

Delay Calculation

	Fixed Delay	Variable Delay
DELAY #1 Total	110 msec	
DELAY #2		
Coder Delay G.729	25 msec	
Packetization Delay (Included in Coder Delay)		
Max Queuing Delay 2 Mbps Trunk		.7 msec
Serialization Delay 2 Mbps Trunk	0.1 msec	
Propagation Delay (Private Lines)	5 msec	
Dejitter Buffer	50 msec	
Delay #2 Total	80 msec	
Total Delay	190 msec	



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

78

Other Useful Voice QoS Schemes in IP

- **Custom Queuing, Priority Queuing and Weighted Fair Queuing (WFQ)**
- **Resource Reservation Protocol (RSVP)**
- **IP Precedence Bit setting in the ToS Field of the IP Header**
- **Compressed Real Time Protocol (CRTP)**

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

79

Summary

- **Voice traffic engineering principles still apply**
- **Packet-based voice trunks can provide efficiency with high quality if properly engineered**
- **The biggest impact on voice quality over a data network will be as a result of the delay and delay variation**

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

80

Repeat: Voice Is Not A Network



- Voice is an Application
- Complete understanding of Voice Application fundamentals helps us to design and build better Networks

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

81

Agenda

- Basic Analog Telephony
- Basic Digital Telephony
- Voice Coding and Compression Techniques
- Voice Transport and Delay
- Supplemental Slides: Digital Voice Signaling Techniques

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

82

Digital Voice Signaling Techniques

- ISDN
- Q.930/Q.931
- Signaling System 7
- Voice addressing

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

83

ISDN

- **Integrated Services Digital Network**

Part of a network architecture

Definition for the access to the network

Allows access to multiple services
through a single access

- **Standards-based**

ITU recommendations

Proprietary implementations

401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com


84

Network Access

Traditional Access



ISDN Access



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

85

Terminology

- **B channel “bearer channel”**
 - 64 kbps**
 - Carries information (voice, data, video, etc.)**
 - DS-0**

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

86

Terminology (Cont.)

- **D channel “signaling channel”**
 - 16 Kbps or 64 Kbps**
 - Carries instructions between customer equipment and network**
 - Carries information**
 - Can also carry packet switch data (X.25) for the public packet switched network**

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

87

Terminology (Cont.)

- **BRA/BRI (Basic Rate Access/ Basic Rate Interface)**
 - 2 B + D**
 - 2 x 64 Kbps + 16 Kbps = 144 Kbps**
(not including overhead)
 - Designed to operate using the average local copper pair**

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

88

Terminology (Cont.)

- **PRA/PRI (Primary Rate Access/Primary Rate Interface)**

23 B + D

23 x 64 Kbps + 64 Kbps (D Channel) + 8 Kbps (Frame Alignment bit) = 1.544 Mbps

Designed to operate using T1/E1

In E1 environments: 30 B + D


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

89

ISDN Reference Points



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

90

ISDN Reference Points

- **NT1**

Terminates local loop

Coding and transmission conversion

Maintenance and performance monitoring

Functions as a CSU

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

91

ISDN Reference Points (Cont.)

- **TE1**

ISDN compatible equipment

- **TE2**

Non-ISDN compatible equipment

Requires TA

- **TA**

Interfaces available for different TE2

E.g. RS-232, X.21, V.35, PC-Bus, video, etc.

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

92

ISDN Reference Points (Cont.)

- **NT2**

Typically a PBX

Provides switching functions

Handles Layer 2 and Layer 3 protocols

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

93

Access to ISDN

- **At the S-reference point:**

RJ-45 (receive and transmit pair)

**Optional power can be provided
for TE devices**

Distance:

1 Km (1 x TE only),

200 m (8 x TE), 500 m (4 x TE)

**When more than one TE, wires
act as a bus**

CSMA/CD

**Limitation: cannot have an
extension phone**

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

94

Access to ISDN

- **At the U-Reference point (BRA)**

Standards differ NA, France,
UK vs. Germany vs. Japan

In North America, designed to use as
much of existing copper plant available

Two wire, unloaded local loops are
99% of total

Up to 5.5 Km loop length

- **At the U-Reference point (PRA)**

T1/E1 standard

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

95

D Channel

- **ISDN Access Protocols are carried in the D channel**

- **Layer 2 and Layer 3 protocol specifications**

Protocol specifications are identical for BRA and PRA

- **Layer 2, Q.920/921, LAP-D**

Supports the communications for Layer 3

Maintains the connections between devices

- **Layer 3, Q.930/931**

Call setup, call supervision, call tear down, and
supplementary services

Uses standard set of messages to communicate


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

96

D-Channel Encapsulation



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

97

ISDN CCS (Q.930/931) Messages

Call Establishment

- Alerting
- Call proceeding
- Connect
- Connect ack
- Progress
- Setup
- Setup ack

Call Information

- Hold
- Hold ack
- Hold reject
- Resume
- Resume ack
- Resume reject
- Retrieve
- Retrieve ack
- Retrieve reject
- Suspend
- Suspend ack
- Suspend reject
- User information

Call Clearing

- Disconnect
- Release
- Release complete
- Restart
- Restart ack

Miscellaneous

- Congestion control
- Facility
- Information
- Notify
- Register
- Status
- Status inquiry


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

98

Public ISDN and Signaling System 7



DSS1 Is a Public ISDN Protocol


401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

99

ISDN and SS7 "The Bridge Between the Islands"



401
0985_05f9_c1


© 1999, Cisco Systems, Inc.

www.cisco.com

100

Cisco Systems Confidential

SS7 Components




401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

101

Network Addressing



401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

102

Cisco Systems Confidential

Agenda

- **Basic Analog Telephony**
- **Basic Digital Telephony**
- **Voice Coding and Compression Techniques**
- **Voice Transport and Delay**
- **Supplemental Slides: Digital Voice Signaling Techniques**

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

103

Thank You!

- **Q & A**
- **Please Fill Out Evaluation Forms**
- **THANK YOU!**

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

104



Please Complete Your Evaluation Form

Session 401

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

105

CISCO SYSTEMS



EMPOWERING THE INTERNET GENERATIONSM

401
0985_05f9_c1

© 1999, Cisco Systems, Inc.

www.cisco.com

106

Cisco Systems Confidential